

Simulator Operating Procedure

1. Turn on the Inverter power supply – Red unit behind the file box
2. Turn on the Monitor by pressing the Far Right button on the bottom of the screen.
3. Open Laptop and push start button in upper left hand corner of the keyboard
4. Left Click to bring up the Log In
5. The log in **PIN 1234 For LoveAir**
6. Double left click on RealFlight Trainer
7. Without internet service you will get a Connection Error
8. Left Click “Start in OFFLINE MODE”
9. Remove Dongle on Right side of the Computer
10. While pressing the end of the Dongle (orange lines) insert the Dongle in the USB port
11. The Dongle should be blinking waiting to be bound
12. While continuing to hold the “A” “BIND” button on the DXs radio, turn on the radio.
13. You will know the radio is bound when the Dongle turns solid Orange and radio BEEPS
14. The simulator should start up. Press and Hold to ensure the radio is off.
15. Click “Fly”
16. If a crash occurs, the “Computer Space Bar” resets the system.
17. The Apprentice should show up. This is the best option for the Trainer Edition of RF
18. The Lower right hand corner indicates the SAFE modes Controlled by switch B.....test it
19. Dual Rates are assigned to Switch “F” – Far right on the top – Back is high
20. Switch “H” is Engine Kill – Good lesson for the student.
21. Throttle setting has a significant effect on these trainers to climb or descend.
22. Test all three modes of flight with the student. Low Rate on Experienced is advised
23. At session completion, please shut off the Transmitter.
24. Close out the Simulator by clicking the Upper right hand corner “X”
25. To shutdown the computer Click the 4 little boxes in the lower left hand corner
26. Click the “Power Circle” and choose Shutdown
27. Shutdown the monitor – lower right bottom corner far right button
28. Turn Off the Inverter Power Supply

If there are any problems, please call or text Jim @ 970-502-7418